TITLE

COMPUTER SYSTEM EQUIPPED WITH A BIOS DEBUGGING CARD

BACKGROUND OF THE INVENTION

Field of the Invention:

5   The present invention relates to a computer system and a corresponding method, and particularly to a computer system supporting insertion of a BIOS debugging card and a corresponding method of the computer. Moreover, the system can be initialized through the debugging card in the event

10   of a ROM BIOS failure.

Description of the Prior Art:

The architecture of most computers is generally defined by functional layers. The lowest layer is the hardware or machine layer. The highest layer is the application program

15   that interfaces with a user. In between the hardware and application program is the system software. The system software itself may be composed of several elements, including: the operating system kernel and shell, device drivers, and, perhaps, a multitasking supervisor.

20   Most architectures also include a low-level software layer between the hardware and the system software, or Basic Input/Output System (BIOS). The BIOS provides primitive I/O services, allowing the system and application software to communicate with the hardware by issuing interrupts. Most

25   computing systems are controlled through the use of interrupts. Interrupts can be generated by the microprocessor, by the system hardware, or by software. The BIOS provides a logical handling of the interrupt signals. When an interrupt occurs, control of the computer is

30   transferred to an interrupt vector which defines the

"segment:offset" address of the routing in BIOS assigned to the given interrupt number.

BIOS Interrupt Service Routines (ISRs) handle interrupts issued by hardware devices. ISRs use registers in the microprocessor and BIOS data areas. The BIOS Device Service Routines (DSRs) handle software interrupts issued by the INT instruction.

In addition to providing the previously described run-time services, the BIOS should be enabled to initialize and configure the computer when the computer is first routed on. The BIOS runs a startup program called the POST program, which performs a number of tasks, including testing random access memory (RAM), conducting an inventory of the hardware devices installed in the computer, configuring hard and floppy disks, keyboard, and serial and parallel ports, configuring other devices installed in the computer such as CD-ROM drives and sound cards, initializing computer hardware required for computer features such as Plug and Play and Power Management, and running setup if requested.

If prior tasks are successful, the Operating System such as DOS, OS/2, UNIX, or Windows '95 is then loaded by the BIOS.

Since the initialization and configuration of the computer system are complicated, the BIOS or operation system possibly fails to be started due to malfunctions or bugs, especially for the BIOS. Accordingly, chipset manufacturers, the main designers of BIOS, are compelled to concentrate effort in debugging the BIOS code.

During debugging of the BIOS, there is an embarrassing situation that the whole system is halted due to any BIOS

error, which make it impossible to debug the BIOS code
through the computer system itself. The debugging of the
BIOS is conventionally done by logic analysis directly
measuring the signals on pins of the chips. This is a time-
5 consuming work.

SUMMARY OF THE INVENTION

The object of the present invention is to provide a
computer system supporting insertion of a BIOS debugging
card, wherein the whole system can be initialized through
10 the debugging card even if ROM BIOS fails.

The present invention provides a method of initializing
a computer system equipped with a debugging system, wherein
the computer system has a CPU, a local, peripheral and
expansion bus, a first and second bridge, and a ROM coupled
15 to the expansion bus and storing first BIOS code, and the
debugging system is coupled to the peripheral bus. The
method comprises the following steps of normal CPU
operation, wherein first data requests directed to the ROM
are routed to the local bus by the CPU, when operating in a
20 debugging mode the CPU directs second data requests to the
debugging system and routes requests to the local bus. The
first or second data requests are transferred from the local
bus to the peripheral bus via the first bridge. The second
bridge responds to the first data requests on the peripheral
25 bus with the first BIOS code stored in ROM to be loaded in
the CPU, and responds to the debugging system with the
second BIOS code stored therein to be loaded in the CPU.

The present invention further provides a computer
system capable of being initialized by a debugging system,
30 comprising a CPU switched between a normal mode wherein

first data requests directed to the ROM are routed to the
local bus by the CPU and a debugging mode wherein second
data requests directed to the debugging system are routed to
the local bus by the CPU, a local, peripheral and expansion
5   bus, wherein the CPU drops first or second data requests to
the local bus and the debugging system is coupled to the
peripheral bus, a ROM coupled to the expansion bus and
storing first BIOS code, to which the first data requests
are directed, a first bridge transferring the first or
10   second data requests from the local to the peripheral bus,
and a second bridge responding the first data requests on
the peripheral bus with the first BIOS code in the ROM to be
loaded in the CPU.

Accordingly, by using a switch to enable or disable the
15   A20 gate of the CPU, the invention can modify the address of
the data requests from the CPU and route the data requests
to the debugging system. Therefore, the BIOS on the ROM can
be ignored and the computer is started by the debugging
system, and then it is possible to analysis and/or correct
20   the errors of the BIOS.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will become more fully understood
from the detailed description given hereinbelow and the
accompanying drawings, given by way of illustration only and
25   thus not intended to be limitative of the present invention.

FIG. 1 is a diagram showing a computer system equipped
with a BIOS debugging card according to one embodiment of
the invention.

FIG. 2 is a diagram showing timing of the signals used
30   in the computer system of FIG. 1.

DETAILED DESCRIPTION OF THE INVENTION

Referring now to FIG. 1, a personal computer system
equipped with a debugging system is shown with the
components being represented in block diagram form.   The
5   various components and buses of the computer system are
typically formed on a system board or motherboard, which are
well known and thus not shown.   The motherboard provides the
necessary wiring, card slots and other connections and
various circuit components, such as capacitors and
10   resistors, to form the system.   A personal computer system
typically contains a CPU 10, based on a microprocessor such
as an Intel Pentium 4.   The CPU 10 is connected to a CPU
local bus 12, which also may have cache memory 13 connected
thereto.

15   The CPU 10 has a specific A20 gate 101.   Employment of
the A20 gate is explained in the following.   Early CPUs,
such as the 8086, have an address space limit of 1M byte,
thus the CPU provides only 20 address lines A0-A19.   When an
address line reaches full capacity, data stored therein
20   begins to populate the next address line (which is usually
called as wrap around).   Newly designed computer systems
provide a 16M byte address space and use a CPU, such as the
80286, which provides 24 address lines.   For the sake of
compatibility between existing software written for earlier
25   microprocessors, and newer computer systems, a CPU must be
able to operate in two modes, a real mode, and a protected
mode.   In protected mode, the CPU emulates earlier CPUs by
disabling the A20 gate (i.e., the output of the address line
A20 is always 0) to limit the address space to 1M byte.   The
30   latest microprocessors, however, such as the Intel Pentium

4, only operate in real mode wherein the A20 gate is always
enabled.

   In order to route a data request, originally directed
to ROM, to the debugging system, a switching signal is input
5 to the A20 gate. When the switching signal is activated by
a switch 102, the A20 gate is disabled and the address
output from the address lines A20 is set to 0. The forcedly
altered address is assigned to the debugging system. Thus,
the CPU may operate in a debugging mode wherein the data
10 request originally directed to the ROM is routed to the
debugging system. Conversely, if the data request is not
routed to the debugging system, the CPU will operate
normally with the A20 gate enabled.

   The local CPU bus 12 is connected to a peripheral bus
15 18, which in the preferred embodiment is the peripheral
controller interconnect (PCI) bus, by the memory
controller/peripheral bus host bridge (MC/PBHB) logic chip
20, known as the "north bridge".

   Various devices, such as a video device 22, can be
20 connected to the peripheral bus 18. An interface card 24
for interconnecting the computer system with another
computer system 4 for debugging is also connected to the
peripheral bus 18.

   The PCI bus 18 is connected through the PCI-to-
25 expansion bus bridge 28, known as the "south bridge", to an
expansion bus 30. The expansion bus 30 can be either a bus
incorporating Micro Channel architecture or an ISA bus. The
south bridge 28 has an address decoder 283 for the ROM 16,
such as for decoding the addresses of the ROM 16. When CPU
30 10 drops a data request directed to the ROM 16, the PCI to

expansion bus bridge 28 handles the reading of the ROM 16 so
that the CPU will read the data from the ROM 16 on the
expansion bus through both the PCI to expansion bus bridge
28 and the MC/PBHB logic chip 20.

5   Various slots 32a, 32b and 32c, are provided for
connecting different devices to the expansion bus 30.
Additionally, a slot 34 for connecting card 15 having ROM 16
is provided on the expansion bus 30. The ROM 16 stores the
BIOS code having the initialization instructions or code.

10   FIG. 2 shows how the represented signals initialize the
computer system by the BIOS ROM 16 or the debugging system
respectively. First it should be noted that the
specification for the PCI bus indicates the various signals
that are available on the PCI bus at the MC/PBHB logic chip
15   20. Only the signals that are relevant to the present
invention are shown in FIG. 2 in various configurations.

     CLK indicates the clock signal which is available from
the system, and RESET indicates a reset signal which on
reset first goes high and then defaults low.

20   If the CPU routes a data request to the local bus 12
for a read cycle of the ROM 16 (normal mode) or the
debugging card 24 (debugging mode), the ROMSEL$ provided by
the MC/PBHB activates the logic chip 20. As used herein and
according to convention, a "$" after a signal designation
25   means "active low". The address of the directed device (ROM
or debugging card) will be presented on the PCI bus
according to PCI bus protocol, together with control signals
to indicate that a memory read cycle is requested. According
to PCI bus protocol, the directed device must activate the
30   DEVSEL$ contact, within three clock cycles for an active

decode, after the address phase for that cycle. Thus, when
the CPU operates in the normal mode, the PCI-to-expansion
bus bridge 28 uses ROMSEL$ signal driven from the MC/PBHB as
an address decode to allow a DEVSEL$ within the three clock
5   cycles after the address phase and retrieves the BIOS code
in the ROM 16 corresponding to the address for loading the
BIOS code in the CPU 10. On the other hand, when the CPU
operates in the debugging mode, the PCI-to-expansion bus
bridge 28 does not respond to ROMSEL$ signal but instead,
10   the interface card 24 responds to ROMSEL$ signal with a
DEVSEL$ within the three clock cycles after the address
phase and retrieves its own BIOS code corresponding to the
address for loading the BIOS code in the CPU 10.

     Accordingly, from the previous description, it is noted
15   that the data request for the BIOS code is routed to the
debugging system when the CPU 10 is switched to debugging
mode. The debugging system takes the place of the south
bridge 28 to respond to the signal ROMSEL$ and loads the
BIOS code stored in the debugging system in the CPU 10.
20   Thus, even if the BIOS code in the ROM 16, the ROM 16 or the
south bridge 28 fails, it can be skipped by switching the
CPU 10 to the debugging mode and the computer system is
initialized by the debugging system. Further, the debugging
card 24 may be connected to another computer system 4
25   through which the BIOS code in the debugging card 24 can be
programmed.

     Initializing the computer system by the debugging
system, has the following advantages. Software applications
may be installed in the computer system 4 to read data in
30   the register of the CPU 10 during initialization.

Conventionally, it is possible to read register data only by
logic analysis or signal probing. If the south bridge 28
and ROM 16 function normally but the BIOS code in the ROM 16
fails, the BIOS code may be read by the computer system 4

5   through the debugging card for debugging. If the south
bridge 28 and ROM 16 function normally but the BIOS code in
the ROM 16 fails, the ROM 16 may be reprogrammed through the
computer system 4.

In conclusion, the present invention provides a

10   computer system capable of being initialized by a BIOS
debugging card. The data request for BIOS code is routed to
the debugging card when the CPU 10 is switched to the
debugging mode. The debugging card on the PCI bus, instead
of the south bridge, responds to the data request from the

15   CPU, which skips the ROM storing the BIOS code. Thus, even
if the BIOS code or ROM fails, the system can be initialized
through the debugging card.

The foregoing description of the preferred embodiments
of this invention has been presented for purposes of

20   illustration and description. Obvious modifications or
variations are possible in light of the above teaching. The
embodiments were chosen and described to provide the best
illustration of the principles of this invention and its
practical application to thereby enable those skilled in the

25   art to utilize the invention in various embodiments and with
various modifications as are suited to the particular use
contemplated. All such modifications and variations are
within the scope of the present invention as determined by
the appended claims when interpreted in accordance with the

breadth to which they are fairly, legally, and equitably
entitled.